



LED emergency pack | 10 - 60V | 70mA | auto test



Autotest is a function that provides emergency lighting for automatic periodic testing of the light source, electronics and battery. This is a protocol that complies with the international standard IEC62034.

The luminaire has the following tests

1. Test after commissioning: as soon as the luminaire is connected for the first time. The batteries are charging for 24 hours, after 24 hours a full autonomy test takes place. After that, the batteries are recharging again for 24 hours.
2. Short function test: for 3 seconds the luminaire tests (after pressing and releasing the test button) the condition of battery, electronics and light source.
3. Monthly function test: automatic 3-minute monthly test.
4. Annual autonomy test: 3-hour automatic, annual, full autonomy test.

Article number:	600-028
CHANGED_LAST:	29-01-2024
Brand:	Tronix Lighting
Type:	Accupacks
ETIM Group:	EG000030 - Accessories for lighting
ETIM Classes:	EC000471 - Emergency unit for luminaire
SYNONYM:	Conversion kit, Emergency unit for luminaire, Installation set





Feature

Lamp type:	LED	With remote switch connection:	No
Power:	4 W	Nominal voltage:	200 ~ 240 V
Monitoring equipment:	Automatic self test	Protection class:	II
Wiring system:	Continuous circuit/emergency circuit	Nominal operation time:	3 ~ 3 h

Packaging data

Weight	440 gr
Width	127 mm
Height	65 mm
Length	190 mm
Customs code	8507302090

